

Installation Guide: QX-4500 DSP Control for Windows 10 & Windows 11

1. Navigate to the start menu, and whilst holding the SHIFT key, select the 'Restart' option.

() Shut down
() Shut down () Restart

2. Once the system reboots, you will be presented with an options screen. Choose the 'Troubleshoot' option from the menu.

	Choose an option	า ง
	Troubleshoot Reset your PC or see advanced options	
	Turn off your PC	

3. Then click 'Advanced Options'

©	Troubleshoot	
	Reset this PC Lets you choose to keep or remove your personal files, and then reinstalls Windows	
	Advanced options	



4. Under the Advanced Options select Startup Settings.



5. Then click the **Restart** button to reboot your PC on the "Startup Settings" screen.

¢	Startup Settings	
	Restart to change Windows options such as:	
	Enable low-resolution video mode Enable debugging mode Enable debugging mode Enable boot logging	
	 Enable Safe Mode Disable driver signature enforcement Disable early-launch anti-malware protection 	
	Disable automatic restart on system failure	
		Restart

6. After that, you will see the "Startup Settings" on your monitor. Press the "**7**" key from the keyboard to activate the "Disable driver signature enforcement" option.



7. Your computer will now reboot, and the Quest Engineering DSP Control software can be installed without error.

When downloading the software, ensure to choose the 64-bit version. This should be compatible with any recent computer running Windows 10 or 11.